

## Data sheet for Power Module

Article No. : **6SL3310-1TE32-6AA3**



Figure similar

Client order no. :  
Order no. :  
Offer no. :  
Remarks :

Item no. :  
Consignment no. :  
Project :

Rated data	
Line voltage	3 AC 342 ... 528 V
Type rating <sup>1)</sup>	
For $I_L$ (50 Hz 400 V)	132 kW
For $I_H$ (50 Hz 400 V)	110 kW
For $I_L$ (60 Hz 460 V)	200 hp
For $I_H$ (60 Hz 460 V)	200 hp
Output current	
Rated current $I_N$	260 A
Base-load current $I_L$ <sup>2)</sup>	250 A
Base load current $I_H$ <sup>3)</sup>	233 A
Maximum current $I_{max}$	375 A
Input current	
Rated input current $I_N$	284 A
Maximum input current $I_{max}$	410 A
Current drawn	
24 V DC auxiliary power supply	0.8 A
Pulse frequency	
Rated frequency	2 kHz
Pulse frequency, max.	
Without current derating	8 kHz
Power loss, max. <sup>4)</sup>	
at 50 Hz 400 V	3.27 kW
at 60 Hz 460 V	3.36 kW

General technical specifications	
Cooling air requirement	0.23 m <sup>3</sup> /s
Sound pressure level $L_{pA}$ (1 m) at 50/60 Hz	71 dB / 71 dB
Minimum short-circuit current <sup>5)</sup>	3,600 A
Line length, max. <sup>6)</sup>	
Shielded	300 m (984.25 ft)
Unshielded	450 m (1,476.38 ft)

Connections	
Line connection	
U1, V1, W1	M10 screw
Conductor cross-section, max. (IEC)	2 x 185 mm <sup>2</sup>
Motor connection	
U2/T1, V2/T2, W2/T3	M10 screw
Conductor cross-section, max. (IEC)	2 x 185 mm <sup>2</sup>
PE1/GND connection	
Design	M10 screw
Conductor cross-section, max. (IEC)	2 x 185 mm <sup>2</sup>
PE2/GND connection	
Design	M10 screw
Conductor cross-section, max. (IEC)	2 x 185 mm <sup>2</sup>
Mechanical data	
Degree of protection	IP20 / UL open type
Frame size	FX
Net weight	104 kg (229.28 lb)
Dimensions	
Width	326 mm (12.8 in)
Height	1,400 mm (55.12 in)
Depth	356 mm (14.02 in)

<sup>1)</sup>Rated output of a typ. 6-pole standard induction motor based on  $I_L$  or  $I_H$  with 400 V 3 AC 50 Hz (kw) or 460 V 3 AC 60 Hz (hp).

<sup>2)</sup>The base load current  $I_L$  is based on a duty cycle of 110% for 60 s or 150% for 10 s with a duty cycle period of 300 s.

<sup>3)</sup>The base load current  $I_H$  is based on a duty cycle of 150% for 60 s or 160% for 10 s with a duty cycle duration of 300 s.

<sup>4)</sup>The specified power loss represents the maximum value at 100% utilization. The value is lower under normal operating conditions.

<sup>5)</sup>Current required for reliably triggering protective devices.

<sup>6)</sup>Longer cable lengths for specific configurations are available on request. For additional information, please refer to the SINAMICS Low Voltage Engineering Manual.