













Round Extension and Fixture Boxes*	Outside Diameter			Color	
	4.75 inches	5.50 inches	6.375 inches		
Extension Box with Open Base For mounting on 3.25 in. (83.00) or 4 in. (102.00) conduit boxes or other recessed outlets.		HBL5737IV A: 1.02" (26.00) B: 4.75" (120.65)	HBL5737AIV A: 1.02" (26.00) B: 5.50" (140.00)	HBL5739AIV A: 1.02" (26.00) B: 6.375" (162.00)	Ivory
Fixture Box with Solid Base To hang fixtures. Cover takes any device with mounting screw centers of 2.75 in. (70.00), 3.5 in. (89.00) and 4.06 in. (103.00). Can be used as a pull or junction box when used with HBL5736IV (blank cover).		HBL5738IV A: 1.02" (26.00) B: 4.75" (120.65)	HBL5738AIV A: 1.02" (26.00) B: 5.50" (140.00)	HBL5739IV A: 1.02" (26.00) B: 6.375" (162.00)	Ivory
Other Round Boxes and Covers*					
Outlet Box For devices with mounting screw centers of 1.47 in. (37.00), 1.63 in. (41.00), 1.69 in. (44.00) or 1.84 in. (46.00). Will take device that mounts on G or H type conduit fittings.			HBL5733IV A: 1.02" (26.00) B: 3.00" (76.00)		Ivory
Blank Cover For use with HBL5733IV. Has 1/2 in. trade size KO in center.			HBL5731IV A: .24" (6.10) B: 2.40" (60.96)		Ivory
Blank Cover For use with HBL5735IV, HBL5737IV, HBL5737AIV, HBL5739AIV, HBL5738IV, HBL5738AIV and HBL5739IV. Has 1/2 in. trade size KO in center.			HBL5736IV A: .38" (9.75) B: 4.19" (106.30)		Ivory
Fanbox with Solid Base Cover accepts fan bracket with mounting centers of 3.2 in. (81.00). Rated for fans and fixtures up to 50 lbs.			HBL5738AFIV A: 1.02" (26.00) B: 4.76" (120.90)		Ivory
Round Fixture Box for Audible Alarms For installing round audible alarms.			HBL5739AABIV A: 1.62" (41.15) B: 6.50" (165.10)		Ivory

*Note: Use catalog number **HBL5791** for connecting 1/2 in. EMT to all HBL5700 Series round boxes (except **HBL5733IV** and **HBL5739AABIV**).

HBL500 and HBL750 Single Channel Metal Raceway

Specialty Boxes*	Catalog Number	Color
Extension Box For extensions from existing flush switch and receptacle boxes	HBL5751IV A: 4.54" (115.32) B: 2.82" (71.63) C: 1.375" (35.00) HBL5751AIV A: 4.54" (115.32) B: 2.82" (71.63) C: 1.75" (44.45)	Ivory Ivory
Blank Extension Box For extensions from existing flush switch and receptacle boxes where it is desired to blank original outlet.	HBL5760IV A: 4.54" (115.32) B: 2.82" (71.63) C: 1.13" (28.70)	Ivory
Low Profile Switch and Receptacle Box For low profile switches and receptacles. Base has ½ in. trade size KOs.	HBL5748SIV A: 4.54" (115.32) B: 2.82" (71.63) C: 1.13" (28.70)	Ivory
Combination Switch and Receptacle Box For connecting to surface runs of ½ in. trade size conduit, one raceway twistout on each side and three raceway twistouts on top and bottom.	HBL5745IV A: 4.54" (115.32) B: 2.82" (71.63) C: 1.375" (35.00)	Ivory
Utility Box For use as a tee, cross, pull box, junction box or blank box. Base has ½ in. trade size KOs.	HBL57242IV A: 4.12" (104.78) B: 2.00" (50.80) C: 1.39" (35.31)	Ivory
Alarm Device Box For surface mounting of alarm devices and safety signals. Fits 4 in. (102.00) square boxes.	HBL5752IV HBL5752R A: 4.54" (115.32) B: 4.64" (117.86) C: 1.375" (35.00)	Ivory Red
Extra Deep Alarm Device Box For surface mounting of alarm devices and safety signals. Cover is 2.75 in. (70.00) deep. Fits 4 in. (102.00) square boxes.	HBL5753IV HBL5753R A: 4.54" (115.32) B: 4.64" (117.86) C: 2.75" (70.00)	Ivory Red
Distribution Box Twistouts permit use of three parallel raceway runs on each side. Cover takes devices with mounting screw centers of 2.75 in. (70.00), 3.5 in. (89.00), 4.0625 in. (103.00) and canopy fixture not larger than 4.625 in. (117.00). Can be used with HBL5736IV (blank cover) to create junction box.	HBL5735IV A: 4.54" (115.32) B: 4.64" (117.86) C: 1.375" (35.00)	Ivory

*Note: Use catalog number **HBL5791** for connecting ½ in. EMT to all HBL5700 Series rectangular boxes.